

2051nm High Power PM BP Filter/Tap Hybrid

FEATURES

- High Isolation
- Low Insertion Loss
- Epoxy-Free Optical Path
- High Reliability and Stability
- Low Profile Packaging

APPLICATIONS

- Broadband Systems
- Optical Amplifying Systems
- Telecommunication Networks
- Metro Networks
- CATV Networks



SPECIFICATIONS

Parameters	Unit	Value
Center Wavelength	nm	2051
Min. Pass Band Width @ 0.5dB	nm	5.0
Excess Loss	dB	≤1.8
Stop Band @25dB	nm	1970-2040 & 2062-2100
Tap Ratio	%	1+/-0.6%, 2+/-0.8%, 5+/-1.0%, 10%, 20%, 30%, 50%
Tap Position	F Type (Forward)	Tap is before Bandpass Filter, Y Type (3-port)
	B Type (Backward)	Tap is after Bandpass Filter, Y Type (3-port)
	X Type	Tap is after Bandpass Filter, 4-port, (Blocked Wavelength Guide Out)
Fiber Type at Tap Port or 4 th Port	-	Same Fiber, Corr. SM Fiber or 50/125um MM Fiber
Optical Return Loss	dB	≥50
Extinction Ratio	dB	≥18
Fiber Type	-	PM1550 Panda Fiber or PM1950 Fiber (V)
	-	10/130um PMDC Fiber (O) or 25/250um PMDC Fiber (R)
Fiber Tensile Load	N	5
Max. Optical Power (CW)	W	1, 2, 3, 5, 10
Operating Temperature	°C	0~50
Storage Temperature	°C	-40~85
Package	Stainless Steel Tube (SST)	(Ø)5.5x40 (≤5W); (Ø)6.0x48 (5~8W)
Dimension	Metal Box	(L)90x(W)18x(H)10 (>8W); (L)120x(W)12x(H)10 (≤8W)

- Note:**
- Specifications are for device without connectors; Specifications may change without notice.
 - To add connectors, IL is 0.3dB higher, RL is 5dB lower, ER is 2dB Lower, Connector key is aligned to slow axis.
 - Only guarantee 1W continuous wave (CW) power thru testing for connectors added.
 - Devices for higher optical power or with other type fiber or consigned fiber are also available; Devices can only work in the core of Double Cladding (DC) Fiber, Cladding Power must be stripped before connecting the device.
 - Backward type can only work in slow axis and fast axis is blocked. Suggest to use X type if blocked power is >1W.

ORDERING INFORMATION (PN)

Bandwidth	Tap Ratio	Position	Tap Port Fiber	4th Port Fiber	Optical Power	Package	Fiber Type	Fiber Sleeve	Fiber Length	Connector Type
50-5nm	01=1%	F=F Type	Y=Same Fiber	Y=Same Fiber	1= 1W	M=Metal Box	2=PM1550Fiber	B= Bare fiber	05=0.5m	N=Without Connector
	05=5%	X=X Type	S=Corr. SM Fiber	S=Corr. SM Fiber	5= 5W	Blank for SST	V=PM1950 Fiber	L= Loose Tube	10=1.0m	FC/APC=FC/APC Connector
	10=10%	Blank for B Type	5=50/125um Fiber	5=50/125um Fiber	10=10W	or >8W	O=10/130 PMDC Fiber	2= 2mm Cable	15=1.5m	LC/PC=LC/PC Connector
	50=50%			Blank for F&B Type	20=20W		R=25/250 PMDC Fiber	3= 3mm Cable	20=2.0m	SC/UPC=SC/UPC Connector