

1020~1080nm Filter Coupler for Pulse

FEATURES

- ▣ Low Excess Loss
- ▣ Various Splitting Ratio
- ▣ Wide Passband
- ▣ High Stability and Reliability
- ▣ Epoxy Free Optical Path

APPLICATIONS

- ▣ Optical Amplifier
- ▣ Optical Networks
- ▣ Power Monitoring
- ▣ Fiber Sensor
- ▣ Lab



SPECIFICATIONS

Parameter	Unit	1x2 Type			2x2 Type		
Center Wavelength	nm	1020, 1030, 1040, 1053, 1064, 1080					
Bandwidth	nm	+/-20nm or customer specify					
Split Ratio	-	1:99	2:98	5:95	10:90	40:60	50:50
Tap Ratio	-	1±0.5%	2±0.6%	5±1.0%	10%	40%	50%
Excess Loss	Max.	dB			1.4		
Uniformity	Max.	dB			0.8		
PDL	dB	≤0.15					
Optical Return Loss	dB	≥50					
	Tap Port	-	Same Fiber or 50/125um MM Fiber				
Fiber Type	Thru Port	-	HI1060 Fiber or 10/125um SC Fiber (E) 10/125um DC Fiber (O), 15/130um DC Fiber (W) 20/130um DC Fiber (Q) or 25/250um DC Fiber (R)				
Fiber Tensile Load	N	5					
Max. Average Optical Power	W	0.3, 0.5, 1, 2, 3, 5, 10, 15, 20, 30, 50, 60, 80, 100					
Max. Peak Power for pulse	kW	0.1, 1, 2, 3, 5, 10, 20					
Operating Temperature	°C	0~50					
Storage Temperature	°C	-40~85					
Package	Stainless Steel Tube (SST)	mm	∅5.5x ^L 35 (≤5W); ∅6.0x ^L 50 (5~10W)				
Dimension	Metal Box	mm	^L 90x ^W 12x ^H 10 (>10W); ^L 120x ^W 12x ^H 10 (≤10W)				

- Note:**
1. Specifications are for device without connectors; Specifications may change without notice.
 2. To add connectors, IL is 0.5dB higher, RL is 5dB lower.
 3. Only guarantee 1W continuous wave (CW) power thru testing for connectors added.
 4. Devices for higher optical power or with other type fiber or consigned fiber are also available; Devices can only work in the core of Double Cladding (DC) Fiber, Cladding Power must be stripped before connecting the device.
 5. Package size may be different for different optical power fiber type and configurations.

ORDERING INFORMATION (PN)

FFFC - NNNN	- NN	N	(C)	-H NN	P NN	-(C)	(C)	C	NN	- CC/CCC
Wavelength	Split Ratio	Type	Tap Port Fiber	Average Power	Peak Power	Package	Fiber Type	Fiber Sleeve	Fiber Length	Connector Type
1030-1030nm	01=1/99	1=1x2	5=50/125um Fiber	03=300mW	01=100W	M=Metal Box	E=10/125 SC Fiber	B= Bare fiber	05=0.5m	N=Without Connector
1053-1053nm	05=5/95	2=2x2	Blank for Same Fiber	1= 1W	1= 1kW	Blank for SST	Q=20/130 DC Fiber	L= Loose Tube	10=1.0m	FC/APC=FC/APC Connector
1064-1064nm	10=10/90			5= 5W	5= 5kW	or >10W	R=25/250 DC Fiber	2= 2mm Cable	15=1.5m	LC/PC=LC/PC Connector
1080-1080nm	50=50/50			10=10W	10=10kW		Blank for HI1060 Fiber	3= 3mm Cable	20=2.0m	SC/UPC=SC/UPC Connector