

1083nm Bandpass Filter/Isolator Hybrid

FEATURES

0

0

0

0

0

APPLICATIONS

- **Broadband Systems** 0
- **Optical Amplifying Systems** 0
- **Telecommunication Networks** 0
- Laser Systems 0
- Research Labs 0



SPECIFICATIONS

High Isolation

Low Insertion Loss

Various Bandwidth

High Optical Power

High Reliability and Stability

Parameters		Unit	Single Stage	Dual Stage		
Center Wavelength		nm	1083			
Min. Pass Band Width	@ 0.5dB	nm	8.0			
Stop Wavelength (ASE)	nm	1000~1076&1090~1150			
Insertion Loss@23°C		dB	≤1.9 ≤3.4			
Signal Isolation (23°C))	dB	≥25 ≥40			
Stop Wavelength	Standard	dB	≥25			
(ASE) Isolation	High Isolation	dB	≥45			
ASE Direction		-	F: Forward, B: Backward, T: Two-way			
Configuration		-	D: 2-port, Y: 3-port, X: 4-port			
Optical Return Loss		dB	≥45			
PDL		dB	≤0.3			
		-	HI1060 Fiber or 10/125um SC Fiber (E)			
Fiber Type	Input&Output		10/125um DC Fiber (0), 15/130um DC Fiber (W)			
преттуре			20/130um DC Fiber (Q) or 25/250um DC Fiber (R)			
	ASE Guide Out (Y/X Type)	-	Same Fiber or MM Fiber			
Max. Optical Power (C)	N)	mW	300			
Operating Temperature	e	°C	0~50			
Storage Temperature		°C	-40~85			
Package Dimension	Stainless Steel Tube (SST)	mm	⁰ 5.5x [⊥] 35			
	Metal Box	mm	[⊥] 120x [₩] 12x ^H 10			

Note: 1. Specifications are for device without connectors; Specifications may change without notice.

2. To add connectors, IL is 0.5dB higher, RL is 5dB lower.

3. Devices for higher optical power or with other type fiber or consigned fiber are also available; Devices can only work in the core of Double Cladding (DC) Fiber, Cladding Power must be stripped before connecting the device.

4. Package size may be different for different optical power and configurations.

ORDERING INFORMATION (PN)

FHBI-1083 _{Stage}	-C NN Bandwidth	(<mark>C</mark>) ASE Type	(C) ASE Iso	- (C) Fwd ASE Fiber	(<mark>C</mark>) - Bwd ASE Fibor	(<mark>C</mark>) Package	(C) Fiber Type	C Fiber Sleeve	NN Fiber Length	-CC/CCC Connector Type
<mark>S=</mark> Single Stage	<mark>80</mark> =8nm	B=Backward	l=High	Y=Same Fiber	Y=Same Fiber	M=Metal Box	E=10/125 SC Fiber	<mark>B=</mark> Bare fiber	<mark>05=</mark> 0.5m	N=Without Connector
D= Dual Stage		T=Two-way	Isolation	A=105/125um Fiber	A=105/125um Fiber	<i>Blank</i> for SST	Q=20/130 DC Fiber	L= Loose Tube	10=1.0m	FC/APC=FC/APC Connector
		<i>Blank</i> for Forward	<i>Blank</i> for	N=None	<mark>5=</mark> 50/125um Fiber		R=25/250 DC Fiber	<mark>2=</mark> 2mm Cable	<mark>15</mark> =1.5m	LC/PC=LC/PC Connector
			Standard	<i>Blank</i> for D Type	<i>Blank</i> for None/D Type		<i>Blank</i> for H11060 Fiber	<mark>3=</mark> 3mm Cable	<mark>20=</mark> 2.0m	SC/UPC=SC/UPC Connector

