

1083nm PM Bandpass Filter for Pulse Power

FEATURES

- High Isolation
- Low Insertion Loss
- High Reliability and Stability
- Various Bandwidth
- High Optical Power

APPLICATIONS

- Broadband Systems
- Optical Amplifying Systems
- Telecommunication Networks
- Laser Systems
- Research Labs



SPECIFICATIONS

Parameters	Unit	Standard	High ER Type
Center Wavelength	nm	1083	
Min. Pass Band Width @ 0.5dB	nm	8.0	
Insertion Loss over Pass Band Wavelength	dB	≤1.2	≤1.4
Stop Wavelength (ASE)	nm	1000~1076&1090~1150	
Stop Wavelength (ASE) Standard	dB	≥25	
Isolation High Isolation	dB	≥45	
ASE Direction	-	F: Forward, B: Backward, T: Two-way	
Configuration	-	D: 2-port, Y: 3-port, X: 4-port	
Optical Return Loss	dB	≥50	
Extinction Ratio	dB	≥18	≥20
Fiber Type	Input&Output	-	PM980 Fiber, PM1060L Fiber (E) or PM1060L-FA Fiber (L) 10/125um PMDC Fiber (O), 15/130um PMDC Fiber (W) 20/130um PMDC Fiber (Q) or 25/250um PMDC Fiber (R)
	ASE Guide Out (Y/X Type)	-	Same Fiber, Corr. SM Fiber or MM Fiber
Fiber Tensile Load	N	5	
Max. Average Optical Power (ASE+Signal)	W	0.3, 0.5, 1, 2, 3, 5, 10, 15, 20, 30, 50, 60, 80, 100	
Max. Peak Power for pulse	kW	0.1, 1, 2, 3, 5, 10, 15, 20	
Max. ASE Average Power	W	0.3, 0.5, 1, 2, 3, 4, 5, 10	
Operating Temperature	°C	0~50	
Storage Temperature	°C	-40~85	
Package Dimension	Stainless Steel Tube (SST)	mm	∅5.5x ^L 35 (≤5W); ∅6.0x ^L 50 (5~10W)
	Metal Box	mm	^L 90x ^W 12x ^H 10 (>10W); ^L 120x ^W 12x ^H 10 (≤10W)

- Note:**
- Specifications are for device without connectors; Specifications may change without notice.
 - To add connectors, IL is 0.5dB higher, RL is 5dB lower, ER is 2dB Lower, Connector key is aligned to slow axis.
 - High ER type can only work in slow axis; Suggest to use Y/X type or H Box if blocked optical power is ≥1W.
 - Only guarantee 1W continuous wave (CW) power thru testing for connectors added.
 - Devices for higher optical power or with other type fiber or consigned fiber are also available; Devices can only work in the core of Double Cladding (DC) Fiber, Cladding Power must be stripped before connecting the device.
 - Package size may be different for different fiber type, optical power and configurations.

ORDERING INFORMATION (PN)

Bandwidth	Type	ASE Type	ASE Iso	Fwd ASE Fiber	Bwd ASE Fiber	Average Power	Peak Power	ASE Power	Package	Fiber Type	Fiber Sleeve	Fiber Length	Connector Type
80-8nm	R=High ER	B=Backward	I=High	Y=Same Fiber	Y=Same Fiber	03=300mW	01=100W	1=1W	M=Metal Box	2=PM980Fiber	B= Bare fiber	05=0.5m	N=Without Connector
	Blank for	T=Two-way	Isolation	S=Corr. SM Fiber	S=Corr. SM Fiber	1=1W	1=1kW	5=5W	H=H Box	E=PM1060L Fiber	L= Loose Tube	10=1.0m	FC/APC=FC/APC Connector
	Standard	Blank for Forward	Blank for	N=None	A=105/125um Fiber	5=5W	5=5kW	10=10W	Blank for SST	Q=20/130 PMDC Fiber	2=2mm Cable	15=1.5m	LC/PC=LC/PC Connector
		Standard	Blank for D Type	Blank for None or D Type		10=10W	10=10kW	Blank for 300mW		R=25/250 PMDC Fiber	3=3mm Cable	20=2.0m	SC/UPC=SC/UPC Connector

