

1290nm PM Bandpass Filter for Pulse Power

FEATURES

- High Isolation
- Low Insertion Loss
- High Reliability and Stability
- Various Bandwidth
- High Optical Power

APPLICATIONS

- Broadband Systems
- Optical Amplifying Systems
- Telecommunication Networks
- Laser Systems
- Research Labs



SPECIFICATIONS

Parameters		Unit	Standard	High ER Type
Center Wavelength		nm	1290	
Min. Pass Band Width @ 0.5dB		nm	15.0	
Insertion Loss over Pass Band Wavelength		dB	≤1.0	≤1.2
Stop Wavelength (ASE)		nm	1250~1278 & 1302-1390	
Stop Wavelength (ASE)	Standard	dB	≥25	
	High Isolation	dB	≥45	
ASE Direction		-	F: Forward, B: Backward, T: Two-way	
Configuration		-	D: 2-port, Y: 3-port, X: 4-port	
Optical Return Loss		dB	≥50	
Extinction Ratio		dB	≥18	≥20
Fiber Type	Input&Output	-	PM1310 Panda Fiber or 10/125um PMDC Fiber NA=0.08 (O)	
			10/130um PMDC Fiber NA=0.15 (O2) or 12/130um PMDC Fiber (T)	
			25/250um PMDC Fiber (R) or 25/300um PMDC Fiber (G)	
	ASE Guide Out (Y/X Type)	-	Same Fiber, Corr. SM Fiber or MM Fiber	
Fiber Tensile Load		N	5	
Max. Average Optical Power (ASE+Signal)		W	0.3, 0.5, 1, 2, 3, 5, 10, 15, 20, 30, 50, 60, 80, 100	
Max. Peak Power for pulse		kW	0.1, 1, 2, 3, 5, 10, 15, 20	
Max. ASE Average Power		W	0.3, 0.5, 1, 2, 3, 4, 5, 10	
Operating Temperature		°C	0~70	
Storage Temperature		°C	-40~85	
Package Dimension	Stainless Steel Tube (SST)	mm	ø5.5x ^L 35 (≤5W); ø6.0x ^L 50(5~10W)	
	Metal Box	mm	H: ^L 90x ^W 12x ^H 10 (>10W);M: ^L 120x ^W 12x ^H 10 (≤10W)	

Note: 1. Specifications are for device without connectors; Specifications may change without notice.

2. To add connectors, IL is 0.3dB higher, RL is 5dB lower, ER is 2dB Lower, Connector key is aligned to slow axis.

3. High ER type can only work in slow axis; Suggest to use Y/X type or H Box if blocked optical power is ≥1W.

4. Only guarantee 1W continuous wave (CW) power thru testing for connectors added.

5. Devices for higher optical power or with other type fiber or consigned fiber are also available; Devices can only work in the core of

Double Cladding (DC) Fiber, Cladding Power must be stripped before connecting the device.

6. Package size may be different for different optical power and configurations.

ORDERING INFORMATION (PN)

FPBP-1290-NNN(C)(C) (C) (C)

(C) -H NN P NN -(NN) - (C)

C

C

NN - CC/CCC

Bandwidth	Type	ASE Type	ASE Iso	Fwd ASE Fiber	Rev ASE Fiber	Average Power	Peak Power	ASE Power	Package	Fiber Type	Fiber Sleeve	Fiber Length	Connector Type
150~15nm	R=High ER	B=Backward	I=High	Y=Same Fiber	Y=Same Fiber	03~300mW	01~100W	1~1W	M=Metal Box	2~PM1310Fiber	B= Bare fiber	05~0.5m	N=Without Connector
	Blank for	T=Two-way	Isolation	S=Corr. SM Fiber	S=Corr. SM Fiber	1~1W	1~1kW	5~5W	H=H Box	0~10/125 PMDC Fiber	L= Loose Tube	10~1.0m	FC/APC=FC/APC Connector
	Standard	Blank for Forward	Blank for	N=None	A=105/125um Fiber	5~5W	10~10kW	10~10W	Blank for SST	T=12/130 PMDC Fiber	2= 2mm Cable	15~1.5m	LC/PC=LC/PC Connector
		Standard	Blank for D Type	Blank for None or D Type		20~20W	20~20kW	Blank for 300mW		G=25/300 PMDC Fiber	3= 3mm Cable	20~2.0m	SC/UPC=SC/UPC Connector

