

1556nm PM BP Filter/Tap Hybrid

FEATURES

- High Isolation
- Low Insertion Loss
- Epoxy-Free Optical Path
- High Reliability and Stability
- Low Profile Packaging

APPLICATIONS

- Broadband Systems
- Optical Amplifying Systems
- Telecommunication Networks
- Metro Networks
- CATV Networks



SPECIFICATIONS

Parameters	Unit	Value	
Center Wavelength	nm	1556	
Min. Pass Band Width @ 0.5dB	nm	2.0, 8.0, 15.0	
Excess Loss	dB	≤1.8	
Stop Band @25dB	2nm Bandwidth	nm	1500~1553 & 1559-1610
	8nm Bandwidth	nm	1500~1548 & 1564-1610
	15nm Bandwidth	nm	1500~1544 & 1568-1610
Tap Ratio	%	1+/-0.6%, 2+/-0.8%, 5+/-1.0%, 10%, 20%, 30%, 50%	
Tap Position	F Type (Forward)	-	Tap is before Bandpass Filter, Y Type (3-port)
	B Type (Backward)	-	Tap is after Bandpass Filter, Y Type (3-port)
	X Type	-	Tap is after Bandpass Filter, 4-port, (Blocked Wavelength Guide Out)
Fiber Type at Tap Port or 4 th Port	-	Same Fiber, Corr. SM Fiber or 50/125um MM Fiber	
Optical Return Loss	dB	≥50	
Extinction Ratio	dB	≥18	
Fiber Type	-	-	PM1550 Panda Fiber or 10/125um PMDC Fiber (O)
	-	-	12/130um PMDC Fiber (T), 20/130um PMDC Fiber (Q)
	-	-	25/250um PMDC Fiber (R) or 25/300um PMDC Fiber (G)
Fiber Tensile Load	N	5	
Max. Optical Power (CW)	mW	300	
Operating Temperature	°C	0~50	
Storage Temperature	°C	-40~85	
Package	Stainless Steel Tube	mm	(Ø)5.5x40
Dimension	Metal Box	mm	(L)120x(W)12x(H)10

- Note:**
- Specifications are for device without connectors; Specifications may change without notice.
 - To add connectors, IL is 0.3dB higher, RL is 5dB lower, ER is 2dB Lower, Connector key is aligned to slow axis.
 - Devices for higher optical power or with other type fiber or consigned fiber are also available; Devices can only work in the core of Double Cladding (DC) Fiber, Cladding Power must be stripped before connecting the device.
 - Backward type can only work in slow axis and fast axis is blocked. Suggest to use X type if blocked power is >1W.

ORDERING INFORMATION (PN)

Bandwidth	Tap Ratio	Position	Tap Port Fiber	4th Port Fiber	Package	Fiber Type	Fiber Sleeve	Fiber Length	Connector Type
20=2nm	01=1%	F=F Type	Y=Same Fiber	Y=Same Fiber	M=Metal Box	2=PM1550Fiber	B= Bare fiber	05=0.5m	N=Without Connector
80=8nm	05=5%	X=X Type	S=Corr. SM Fiber	S=Corr. SM Fiber	Blank for SST	O=10/125 PMDC Fiber	L= Loose Tube	10=1.0m	FC/APC=FC/APC Connector
150=15nm	10=10%	Blank for B Type	5=50/125um Fiber	5=50/125um Fiber		T=12/130 PMDC Fiber	2= 2mm Cable	15=1.5m	LC/PC=LC/PC Connector
	50=50%			Blank for F&B Type		G=25/300 PMDC Fiber	3= 3mm Cable	20=2.0m	SC/UPC=SC/UPC Connector