

# 1040nm PM Tap Isolator Hybrid

## FEATURES

- Low Excess Loss
- Various Splitting Ratio
- Wide Passband
- High Stability and Reliability
- Epoxy Free Optical Path

## APPLICATIONS

- Optical Amplifier
- Optical Networks
- Power Monitoring
- Fiber Sensor
- Lab



## SPECIFICATIONS

Parameter	Unit	Single Stage	Dual Stage
Center Wavelength	nm	1040	
Bandwidth	nm	+/-10	
Split Ratio	%	0.1:99.9, 1:99, 2:98, 5:95, 10:90, 20:80, 30:70, 40:60, 50:50	
Tap Ratio	-	0.1%, 1+/-0.6%, 2+/-0.8%, 5+/-1.0%, 10%, 20%, 30%, 40%, 50%	
Excess Loss	Max.	dB	≤4.0
Peak Isolation	Typ.	dB	28
Min. Isolation (23°C)		dB	≥22
Extinction Ratio		dB	≥18
Working Mode	S Type	-	Tap Input Light before Isolator, Can only work in Slow Axis
	F Type	-	Tap Input Light before Isolator, work in Slow & Fast Axis
	B Type	-	Tap Input Light after Isolator, Can only work in slow axis
Optical Return Loss		dB	≥50
Fiber Type	Tap Port	-	Same fiber, Corr. SM Fiber or 105/125um MM Fiber
	Thru Port	-	PM980 Fiber, PM1060L Fiber (E) or PM1060L-FA Fiber (L)
			10/125um PMDC Fiber (O), 15/130um PMDC Fiber (W)
			20/130um PMDC Fiber (Q) or 25/250um PMDC Fiber (R)
Fiber Tensile Load		N	5
Max. Optical Power (CW)		mW	100
Operating Temperature		°C	0~50
Storage Temperature		°C	-40~85
Package	Stainless Steel Tube (SST)	mm	(Ø)5.5x35
Dimension	Metal Box	mm	(L)120x(W)12x(H)10

- Note:**
1. Specifications are for device without connectors; Specifications may change without notice.
  2. To add connectors, IL is 0.5dB higher, RL is 5dB lower, ER is 2dB Lower, Connector key is aligned to slow axis.
  3. Devices for higher optical power or with other type fiber or consigned fiber are also available; Devices can only work in the core of Double Cladding (DC) Fiber, Cladding Power must be stripped before connecting the device.

## ORDERING INFORMATION (PN)

FPTI-NNNN	- C	C	NN	(C)	-(C)	C	C	NN	-CC/CCC
Wavelength	Stage	Type	Split Ratio	Tap Port Fiber	Package	Fiber Type	Fiber Sleeve	Fiber Length	Connector Type
1040-1040nm	S=Single Stage	S=S Type	01=1/99	S=Corr. SM Fiber	M=Metal Box	2=PM980 Panda Fiber	B= Bare Fiber	05=0.5m	N=Without Connector
	D=Dual Stage	F=F Type	10=10/90	A=105/125um Fiber	Blank for SST	E=PM1060L Fiber	L= Loose Tube	10=1.0m	FC/APC=FC/APC Connector
		B=B Type	30=30/70	Blank for Same Fiber		Q=20/130 PMDC Fiber	2= 2mm Cable	15=1.5m	LC/PC=LC/PC Connector
			50=50/50			R=25/250 PMDC Fiber	3= 3mm Cable	20=2.0m	SC/UPC=SC/UPC Connector