

STATISTICS OF THE STATE

Compliant

1550/1625/1650nm PM WDM Filter for Pulse Power

FEATURES

0

0

ÅPPLICATIONS

Broadband Systems 0 Low Insertion Loss **Optical Amplifying Systems** 0 High Reliability and Stability **Telecommunication Networks** 0

0

- 0 Various Bandwidth 0
- High Optical Power 0

High Isolation

Laser Systems Research Labs 0

SPECIFICATIONS

Parameters		Unit	Standard	High Isolation			
Pass Channel Waveler	igth Range λ1	nm	1500-1580				
Reflective Channel Wa	velength Range $\lambda 2$	nm	1625+/-15, 1620-1660				
Insertion Loss over $\lambda 1$	@ Pass Channel	dB	≤1.0 ≤1.2				
Insertion Loss overλ2	@ Reflective Channel	dB	≤0.8				
Configuration	Ү Туре	-	3-р	ort			
	Х Туре	-	4-port (2x2 WDM)				
Isolation over $\lambda 1 @ Re$	eflective Channel	dB	≥12				
Isolation over $\lambda 2 @ Pa$	ass Channel	dB	≥25	≥45			
Optical Return Loss		dB	≥50				
Extinction Ratio	Standard	dB	≥18				
	High ER Type	dB	≥20				
		-	PM1550 Panda Fiber, 10/125um PMDC Fiber (O),				
Fiber Type			12/130um PMDC Fiber (T), 20/130um PMDC Fiber (Q)				
			25/250um PMDC Fiber (R), 25/300um PMDC Fiber (G)				
Polarization Alignment	:	-	Slow Axis				
Fiber Tensile Load		N	5				
Max. Average Optical	Power	W	0.3, 0.5, 1, 2, 3, 5, 10, 15, 20, 30, 40, 50, 60				
Max. Peak Power for p	oulse	kW	0.1, 1, 2, 3, 5, 10, 15, 20				
Operating Temperatur	e	°C	0~70				
Storage Temperature		°C	-40~85				
Dackago Dimonsion	Stainless Steel Tube (SST)	mm	[∅] 5.5x [∟] 35 (≤5W); [∅] 6.0x [∟] 50 (5~10W)				
Package Dimension	Metal Box	mm	^L 120x ^W 12x ^H 10 (≤10W)				

Note: 1. Specifications are for device without connectors; Specifications may change without notice.


2. To add connectors, IL is 0.3dB higher, RL is 5dB lower, ER is 2dB Lower, Connector key is aligned to slow axis.

3. Only guarantee 1W continuous wave (CW) power thru testing for connectors added.

4. Devices for higher optical power or with other type fiber or consigned fiber are also available; Devices can only work in the core of Double Cladding (DC) Fiber, Cladding Power must be stripped before connecting the device.

5. High ER type can only work in slow axis at pass port.

PACKAGE DIMENSION (>10W)



ORDERING INFORMATION (PN)													
FPWM-	IN NN	- (<mark>C</mark>)	(<mark>C</mark>)	(<mark>C</mark>)	(<mark>C</mark>) ·	H NN	P NN	- (NN)	-(<mark>C</mark>)	С	С	NN -	CC/CCC
Ref Wavelength	Pass Wavelength	Configuration	Mode	Туре	Isolation	Average Power	Peak Power	Average Power (Ref)	Package	Fiber Type	Fiber Sleeve	Fiber Length	Connector Type
<mark>16=</mark> 1650nm	<mark>15</mark> =1550nm	<mark>X</mark> = X Type	M= Mux	H= High ER	I= High Iso	<mark>03</mark> =300mW	<mark>01</mark> =100W	<mark>1</mark> - 1W	M=Metal Box	2=PM1550 Fiber	<mark>B=</mark> Bare Fiber	<mark>05=</mark> 0.5m	N=Without Connector
<mark>62=</mark> 1625nm	<mark>16=</mark> 1650nm	<i>Blank</i> for Y Type	D= Demux	<i>Blank</i> for	<i>Blank</i> for	<mark>1</mark> - 1W	<mark>1-</mark> 1kW	<mark>2</mark> = 2W	<i>Blank</i> for SST	0=10/125 PMDC Fiber	L= Loose Tube	<mark>10-</mark> 1.0m	FC/APC=FC/APC Connector
<mark>15=</mark> 1550nm	<mark>62</mark> =1625nm		<i>Blank</i> for Both	Standard	Standard	<mark>10</mark> -10W	<mark>10</mark> -10kW	<mark>5</mark> =5W	or >10W	T=12/130 PMDC Fiber	<mark>2</mark> =2mm Cable	<mark>15=</mark> 1.5m	LC/PC =LC/PC Connector
						<mark>20</mark> =20W	<mark>20</mark> -20kW	<i>Blank</i> for Sameto Pass	;	R=25/250 PMDC Fiber	<mark>3=</mark> 3mm Cable		SC/UPC=SC/UPC Connector
												Ro	HS

