

750~850nm 2x2 High Power PBC/PBS

FEATURES

0

0

0 High Isolation

ÅPPLICATIONS

0

Broadband Systems 0

Research Labs

- 0 **Optical Amplifying Systems**
- High Reliability and Stability **Telecommunication Networks** 0
- Various Bandwidth 0

Low Insertion Loss

- High Optical Power 0
- Laser Systems 0

SPECIFICATIONS

Parameter		Unit	Value			
Center Wavelength	nm	760, 780, 793, 808	830, 850			
Bandwidth		nm	+/-10			
Insertion Loss (Port 3 to Port 1/2 at Slow	(Typ.)	dB	0.9	0.8		
Axis, Port 4 to Port 1/2 at Fast Axis)	(Max.)	dB	1.6	1.4		
Optical Return Loss		dB	≥45			
Extinction Ratio (for FPDS)	(Typ.)	dB	22			
	(Min.)	dB	18			
Fiber Type of Port 1 & Port 2		-	PM850 Fiber or PM780-HP Fiber			
Fiber Type of Port 3 & Port 4	S Type	-	Corresponding SM Fiber			
	Р Туре	-	Same Fiber to Port1&2, Slow axis align to Port 1 Slow/Fast axis			
	Q Type	-	Same Fiber to Port1&2, Slow axis is 45° to Port 1 Slow/Fast axis			
Fiber Tensile Load		N	5			
Max. Optical Power (CW)		W	1, 2, 3, 5, 10, 15, 20			
Operating Temperature		°C	0~50			
Storage Temperature		°C	-40~85			

Note: 1. Specifications are for device without connectors; Specifications may change without notice.


2. To add connectors, IL is 0.7dB higher, RL is 5dB lower, ER is 2dB Lower, Connector key is aligned to slow axis.


3. Only guarantee 1W continuous wave (CW) power thru testing for connectors added.

4. Devices for higher optical power or with other type fiber or consigned fiber are also available; Devices can only work in the core of Double Cladding (DC) Fiber, Cladding Power must be stripped before connecting the device.

5. Package size may be different for different optical power and fiber type.

LIGHT ROUTE





ORDERING INFORMATION (PN) FPDC=Polarization Beam Combiner; FPDS=Polarization Beam Splitter.

FPDC _ FPDS	NNN	- C	C -	HP NN	- C	С	NN	- CC/CCC
	Center Wavelength	3rd Port Fiber	4th Port Fiber	Optical Power	Fiber Type	Fiber Sleeve	Fiber Length	Connector Type
	<mark>780</mark> =780nm	<mark>S=</mark> S Type	<mark>S=</mark> S Type	<mark>1</mark> - 1W	2=PM850 Fiber	B= Bare fiber	<mark>05=</mark> 0.5m	N=Without Connector
	<mark>793=</mark> 793nm	P=P Type	P=P Type	<mark>5=</mark> 5W	7=PM780HP Fiber	L= Loose Tube	10=1.0m	FC/APC=FC/APC Connector
	<mark>830</mark> =830nm	Q=Q Type	Q=Q Type	10-10W		<mark>2=</mark> 2mm Cable	15=1.5m	LC/PC=LC/PC Connector
	<mark>850=</mark> 850nm			<mark>20</mark> -20W		<mark>3=</mark> 3mm Cable	<mark>20=</mark> 2.0m	SC/UPC-SC/UPC Connector



